

**A. Change of APN setting in GSM handset for
2G & 3G BSNL Mobile subscribers
(effective from 01.11.2009)**

Sl. No.	Service	Existing APN in East Zone	New equivalent APN
1	http browsing with Desktop/Laptop.	gprseast.cellone.in	bsnlnet
2	WAP Browsing.	wapeast.cellone.in	bsnlwap
3	BSNL Portal for <i>toll free</i> browsing wap.cellone.in	portaleast.cellone.in	bsnlportal
4	Video Streaming – Mobile TV	vaseast.cellone.in	bsnlmobiltv
5	MMS	mmseast.cellone.in	bsnlmms
6	BSNL Live for accessing 3G Portal		bsnllive
7	Live Streaming and VoD		bsnlstream

**B. Change of settings in GSM handset for
BSNL Mobile GPRS subscribers (effective
from 01.11.2009)**

Setting Type	(GPRS Internet/HTML)	(GPRS WAP)	(GPRS WAP)	(GPRS STREAM)	(GPRS MMS)	(GPRS WAP)	(GPRS STREAM)
Connection Name	BSNLNET	BSNLWAP	BSNLPORTAL	BSNLTV	BSNLMMS	BSNLLIVE	BSNLSTREAM
Data Bearer	GPRS	GPRS	GPRS	GPRS	GPRS	GPRS	GPRS
Access Point Name	bslnet	bsnlwap	bsnlportal	bsnlmobiltv	bsnlmms	bsnllive	bsnlstream
User Name	Nil	Nil	Nil	Nil	Nil	Nil	Nil
Prompt Password	No	No	No	No	No	No	No
Password	Nil	Nil	Nil	Nil	Nil	Nil	Nil
Authentication	Normal	Normal	Normal	Normal	Normal	Normal	Normal
Homepage	http://www.cellone.in	http://wap.cellone.in	http://wap.cellone.in		http://bsnlmmsc.in:8514	http://bsnllive.net	
Phone IP Address	Automatic	Automatic	Automatic	Automatic	Automatic	Automatic	Automatic
Name Server	Automatic	Automatic	Automatic	Automatic	Automatic	Automatic	Automatic
Proxy Serv. Address	off	10.220.67.131	10.220.67.131	off	10.210.10.11	10.220.67.131	off
Proxy Port Number		8080	8080		8080	8080	

One can change the setting manually. Alternatively, for getting the setting downloaded to your GSM handset, type "Manufacturer <Space> Model Number" & send SMS to code "58355".